



6-Way Narrow Band Power Dividers/Combiners

FEATURES

- ❖ Low Insertion Loss
- ❖ Excellent Amplitude Tracking
- ❖ Low VSWR
- ❖ Excellent Phase Tracking
- ❖ High Isolation
- ❖ High Power Handling
- ❖ Low Profile
- ❖ Wide Operating Temperature Range

SPECIFICATIONS

6-Way Narrow Band Power Dividers/Combiners													
Model Number	Freq (GHz)	Isolation (dB)		Insertion Loss (dB)		Amplitude Balance (dB rms) (Max)	Phase Balance (° rms) (Max)	VSWR				Input Power (Watt)	Outline Figure
		Typ	Min	Typ	Max			Input		Output			
								Typ	Max	Typ	Max		
6DY-0D85	0.8-0.9	23	21	0.5	0.7	0.1	1	1.25:1	1.35:1	1.20:1	1.30:1	15	4
6DY-1D90	1.8-2.0	22	20	0.5	0.7	0.1	1	1.25:1	1.35:1	1.20:1	1.30:1	15	3
6DY-5D65	5.4-5.9	21	19	0.7	0.9	0.15	2	1.30:1	1.40:1	1.25:1	1.35:1	15	2
6DY-9D75	9.5-10	21	19	0.9	1.1	0.15	2.5	1.35:1	1.45:1	1.30:1	1.40:1	15	2
6DY-13D00	12.7-13.3	21	19	1.1	1.3	0.15	3	1.35:1	1.45:1	1.30:1	1.40:1	10	2
6DY-14D25	14-14.5	20	18	1.1	1.3	0.15	3	1.35:1	1.45:1	1.30:1	1.40:1	8	2
6DY-19D50	19.3-19.7	18	16	1.4	1.5	0.25	4	1.40:1	1.50:1	1.35:1	1.45:1	8	1
6DY-20D70	20.2-21.2	18	16	1.5	1.7	0.25	4	1.40:1	1.50:1	1.35:1	1.45:1	8	1
6DY-30D15	29.3-31	17	15	1.7	2.0	0.3	4.5	1.50:1	1.60:1	1.40:1	1.50:1	5	1
6DY-38D30	37-39.6	16	14	2.2	2.5	0.3	5	1.60:1	1.80:1	1.50:1	1.60:1	5	1

- Note 1. Input power rate is at the condition when all the outputs are connected to the loads with 1:25:1 or better VSWR at any phase difference. Higher power rate is available on request.
- Note 2. Standard connectors are SMA for frequency up to 18 GHz, supper SMA for frequency up to 27 GHz and 2.92 mm for frequency up to 40 GHz. Other connector options are available on request.

